

RESEARCH NOTES

NOTE ON MODULATIONAL INSTABILITY OF BOUSSINESQ WAVE TRAINS

S. ROY CHOUDHURY

Department of Mathematics
University of Central Florida
Orlando, FL 32816

(Received September 3, 1991)

ABSTRACT. It is demonstrated that modulational instability may occur in Boussinesq wavetrains for wavenumbers $k^2 > 1$, in contrast to the result found by Shivamoggi and Debnath. Both Whitham's averaged Lagrangian formulation and the technique of Benjamin and Feir are used.

Key Words and Phrases: Modulational stability, Boussinesq wavetrains, nonlinear waves.

1991 AMS Subject Classification: 76E30, 76B15, 76B25

1. INTRODUCTION. The weakly nonlinear stability analysis of periodic wavetrains in fluids and plasmas has been considered by several authors [1]. Shivamoggi and Debnath [2] considered the modulational instability of both the Korteweg-De Vries (KdV) and Boussinesq wavetrains using the variational formulation of Whitham. In this note, we demonstrate that modulational instability may indeed exist for Boussinesq wavetrains, in contrast to the result stated in Ref. [2].

2. MAIN RESULTS. Following the notation of [2], we obtain the averaged Lagrangian (Ref 2, Eq. (4.14)) for the Boussinesq wavetrains:

$$\bar{L} = \left[\frac{1}{2} k^2 (\omega^2 - k^2) + \frac{k^6}{2} \right] \frac{a_1^2}{2} + \left[\frac{k^2}{144} (\omega^2 - k^2) + \frac{k^6}{36} - \frac{k^6}{24} \right] a_1^4. \quad (2.1)$$

Here, ω and k are the angular frequency and wavenumber, respectively. From the Whitham theory of averaged Lagrangians, the wavetrain is modulationally unstable if $\omega_2 < 0$ for a dispersion relation (for nonlinear dispersive wavetrains) of the form

$$\omega = \omega_0(k) + \omega_2(k) a_1^2. \quad (2.2)$$

From (2.1), the dispersion relation $\partial \bar{L} / \partial a_1 = 0$ is:

$$\omega^2 = \frac{2k^4(a_1^2 - 9)}{a_1^2 + 18} + k^2. \quad (2.3)$$

Notice that Eq. (3) differs from the corresponding equation (4.15) of [2]. Treating the amplitude a_1 as small in the weakly nonlinear theory yields:

$$\omega \approx (k^2 - k^4)^{1/2} + \frac{k^2 a_1^2}{12(1 - k^2)}. \quad (2.4)$$

Hence, from (2) and (4)

$$\omega_2 = \frac{k^2}{12(1 - k^2)}. \quad (2.5)$$

Thus, $\omega_2 < 0$ and modulational instability exists in the Boussinesq equation for the range of wavenumbers $k^2 > 1$, unlike the absolute modulational stability found in Ref. 2.

Note that the existence of modulational instability for the Boussinesq equation

$$\phi_{tt} - \phi_{xx} - \phi_{xxxx} - (\phi^2)_{xx} = 0, \quad (2.6)$$

may also be seen by carrying out an analysis similar to Benjamin and Feir [3]. Substituting the modulated solution

$$\phi(x, t) = b_0[1 + \varepsilon(x, t)] \quad (2.7)$$

around the spatially independent Stokes solution b_0 of Eq. (6), and writing

$$\varepsilon(x, t) = \hat{\varepsilon}_{-n}(0)e^{-i(k_n x + \omega t)} + \hat{\varepsilon}_n(0)e^{i(k_n x + \omega t)}, \quad (2.8)$$

We obtain from (6):

$$(-\omega^2 + k_n^2 - k_n^4 + 2b_0 k_n^2) \hat{\varepsilon}_{-n}(0) = 0$$

Clearly, for $\omega = \omega_r + i\omega_i$ and $\omega_r = 0$, the growth rate ω_i is given by:

$$\omega_i^2 = k_n^4 - (1 + 2b_0)k_n^2.$$

Hence, $\omega_i^2 > 0$ and modulational instability may occur for $k_n^2 > (1 + 2b_0)$.

REFERENCES

1. WHITHAM, G.B., Nonlinear Dispersion of Water Waves, *J. Fluid Mech.* **27** (1967) 399-412; LIGHTHILL, M.J., Contributions to the Theory of Waves in Nonlinear Dispersive Systems, *J. Inst. Math. Appl.* **1** (1965) 269-306; BENJAMIN, T.B., Instability of Periodic Wavetrains in Nonlinear Dispersive Systems, *Proc. Roy. Soc. London* **299A** (1967) 59-75.
2. SHIVAMOGGI, B.K. and DEBNATH, L., Modulational Stability of Korteweg-De Vries and Boussinesq Wavetrains, *Int. J. Math. and Math. Sci.* **6** (1983) 811-817.
3. BENJAMIN, T.B. and FEIR, J.E., The Disintegration of Wavetrains in Deep Water, Part I, *J. Fluid Mech.* **27** (1967) 417-430.

Special Issue on Modeling Experimental Nonlinear Dynamics and Chaotic Scenarios

Call for Papers

Thinking about nonlinearity in engineering areas, up to the 70s, was focused on intentionally built nonlinear parts in order to improve the operational characteristics of a device or system. Keying, saturation, hysteretic phenomena, and dead zones were added to existing devices increasing their behavior diversity and precision. In this context, an intrinsic nonlinearity was treated just as a linear approximation, around equilibrium points.

Inspired on the rediscovering of the richness of nonlinear and chaotic phenomena, engineers started using analytical tools from "Qualitative Theory of Differential Equations," allowing more precise analysis and synthesis, in order to produce new vital products and services. Bifurcation theory, dynamical systems and chaos started to be part of the mandatory set of tools for design engineers.

This proposed special edition of the *Mathematical Problems in Engineering* aims to provide a picture of the importance of the bifurcation theory, relating it with nonlinear and chaotic dynamics for natural and engineered systems. Ideas of how this dynamics can be captured through precisely tailored real and numerical experiments and understanding by the combination of specific tools that associate dynamical system theory and geometric tools in a very clever, sophisticated, and at the same time simple and unique analytical environment are the subject of this issue, allowing new methods to design high-precision devices and equipment.

Authors should follow the Mathematical Problems in Engineering manuscript format described at <http://www.hindawi.com/journals/mpe/>. Prospective authors should submit an electronic copy of their complete manuscript through the journal Manuscript Tracking System at <http://mts.hindawi.com/> according to the following timetable:

Manuscript Due	December 1, 2008
First Round of Reviews	March 1, 2009
Publication Date	June 1, 2009

Guest Editors

José Roberto Castilho Piqueira, Telecommunication and Control Engineering Department, Polytechnic School, The University of São Paulo, 05508-970 São Paulo, Brazil; piqueira@lac.usp.br

Elbert E. Neher Macau, Laboratório Associado de Matemática Aplicada e Computação (LAC), Instituto Nacional de Pesquisas Espaciais (INPE), São José dos Campos, 12227-010 São Paulo, Brazil ; elbert@lac.inpe.br

Celso Grebogi, Center for Applied Dynamics Research, King's College, University of Aberdeen, Aberdeen AB24 3UE, UK; grebogi@abdn.ac.uk