

RESEARCH NOTES

NOTE ON HÖLDER INEQUALITIES

SUNG GUEN KIM

Department of Mathematics
Pohang Institute of Science & Technology
P.O. Box 215, Pohang 790-600, Korea

(Received April 13, 1992 and in revised form June 26, 1993)

ABSTRACT. In this note, we show that if m, n are positive integers and $x_{ij} \geq 0$, for $i = 1, \dots, n$, for $j = 1, \dots, m$, then

$$\left(\sum_{i=1}^n x_{i1} \cdots x_{im} \right)^m \leq \left(\sum_{i=1}^n x_{i1}^m \right) \cdots \left(\sum_{i=1}^n x_{im}^m \right)$$

with equality, in case $(x_{11}, \dots, x_{n1}) \neq 0$ if and only if each vector $(x_{1j}, \dots, x_{nj}), j = 1, \dots, m$, is a scalar multiple of (x_{11}, \dots, x_{n1}) . The proof is a straight-forward application of Hölder inequalities. Conversely, we show that Hölder inequalities can be derived from the above result.

KEY WORDS AND PHRASES. The Hölder Inequalities.

1991 AMS SUBJECT CLASSIFICATION CODES. 26D15.

1. MAIN RESULTS.

LEMMA 1. If m, n are positive integers and $x_{ij} \geq 0$, for $i = 1, \dots, n$, for $j = 1, \dots, m$, then

$$\left(\sum_{i=1}^n x_{i1} \cdots x_{im} \right)^m \leq \left(\sum_{i=1}^n x_{i1}^m \right) \cdots \left(\sum_{i=1}^n x_{im}^m \right)$$

with equality, in case $(x_{11}, \dots, x_{n1}) \neq 0$ if and only if each vector $(x_{1j}, \dots, x_{nj}), j = 1, \dots, m$, is a scalar multiple of (x_{11}, \dots, x_{n1}) .

PROOF. Use induction on m . When $m = 1$, the above inequalities are trivial. Suppose that the above inequalities hold with $m - 1$. Then it follows that

$$\begin{aligned} \left(\sum_{i=1}^n x_{i1} \cdots x_{im} \right)^m &\leq \left\{ \sum_{i=1}^n (x_{i1} \cdots x_{im-1})^{\frac{m}{m-1}} \right\}^{\frac{m-1}{m}} \cdot \left\{ \sum_{i=1}^n x_{im}^m \right\}^{\frac{1}{m}}, \quad (\text{by Hölder Inequalities}) \\ &= \left\{ \sum_{i=1}^n x_{i1}^{\frac{m}{m-1}} \cdots x_{im-1}^{\frac{m}{m-1}} \right\}^{\frac{m-1}{m}} \cdot \left\{ \sum_{i=1}^n x_{im}^m \right\}^{\frac{1}{m}} \\ &\leq \left\{ \sum_{i=1}^n x_{i1}^{\frac{m}{m-1} \cdot (m-1)} \cdots \sum_{i=1}^n x_{im-1}^{\frac{m}{m-1} \cdot (m-1)} \right\}^{\frac{1}{m}} \cdot \left\{ \sum_{i=1}^n x_{im}^m \right\}^{\frac{1}{m}}, \quad (\text{by Induction Hypothesis}) \\ &= \left\{ \sum_{i=1}^n x_{i1}^m \cdots \sum_{i=1}^n x_{im-1}^m \cdot \sum_{i=1}^n x_{im}^m \right\}^{\frac{1}{m}} \end{aligned}$$

Therefore the proof is complete.

Note that the above inequalities have been deduced using Hölder Inequalities. We can also deduce Hölder Inequalities by using the above inequalities.

THEOREM 1. Given $p_1, \dots, p_n \in \mathbb{R}$ with $p_k > 1$, for each $k = 1, \dots, n$ and $\sum_{k=1}^n \frac{1}{p_k} = 1$ and given $a_1, \dots, a_n > 0$, we have the following inequality

$$a_1 \cdots a_n \leq \sum_{k=1}^n \frac{a_k^{p_k}}{p_k}.$$

PROOF. First we prove this theorem when all p_k 's are rational. Write $p_k = \frac{c_k}{b_k}$ for some $b_k, c_k \in \mathbb{N}$ for $1 \leq k \leq n$. Let $m = 2 \cdot \text{lcm}(c_1, \dots, c_n)$. Let $q_k = \frac{m}{p_k}$ for $1 \leq k \leq n$. It is clear that $q_k \geq 2$ for $1 \leq k \leq n$. Let $x_k = a_k^{\frac{q_k}{p_k}}$ for $1 \leq k \leq n$. Let $S: \mathbb{R}^m \rightarrow \mathbb{R}^m$ be the mapping defined by

$$S(y_1, y_2, \dots, y_m) = (y_m, y_1, y_2, \dots, y_{m-1})$$

for $(y_1, y_2, \dots, y_m) \in \mathbb{R}^m$. Define m vectors Z_1, \dots, Z_m by

$$Z_1 = \left(\underbrace{x_1, \dots, x_1}_{q_1 - \text{times}}, \underbrace{x_2, \dots, x_2}_{q_2 - \text{times}}, \dots, \underbrace{x_m, \dots, x_m}_{q_m - \text{times}} \right)$$

and $Z_i = S(Z_{i-1})$ for $2 \leq i \leq m$. Applying the Lemma 1 to the m vectors Z_1, \dots, Z_m , we have

$$m \cdot x_1^{q_1} \cdots x_n^{q_n} \leq q_1 \cdot x_1^m + \cdots + q_n \cdot x_n^m \quad (1.1)$$

and equality holds if and only if $x_1 = x_k$ for $2 \leq k \leq n$.

By substituting $x_k^m = a_k^{p_k}$ ($1 \leq k \leq n$) into both sides in (1.1), we have

$$a_1 \cdots a_n \leq \sum_{k=1}^n \frac{a_k^{p_k}}{p_k},$$

and equality holds if and only if $a_1^{p_1} = a_k^{p_k}$ for $2 \leq k \leq n$. Now, let us show the theorem when all p_k 's are real. We can choose n sequences of rational numbers $\{r_{1j}\}, \dots, \{r_{nj}\}$ satisfying $r_{kj} > 1$ for $1 \leq k \leq n$, all $j \in \mathbb{N}$ and $\sum_{k=1}^n \frac{1}{r_{kj}} = 1$ for each $j \in \mathbb{N}$ and $r_{kj} \rightarrow p_k$ as $j \rightarrow \infty$, for $1 \leq k \leq n$. By the above argument, for each $j \in \mathbb{N}$, we have

$$a_1 \cdots a_n \leq \sum_{i=1}^n \frac{a_k^{p_k}}{r_{kj}}$$

Taking the limit as $j \rightarrow \infty$, the result follows.

Hölder Inequalities follow from Theorem 1 in the usual way, that can be found in most text books. From Lemma 1 and Theorem 1, we know that the following form of inequalities is essential for the Hölder inequalities: If n is a positive integer and $x_{ij} \geq 0$, for $i = 1, \dots, n$, for $j = 1, \dots, n$, then

$$\left(\sum_{i=1}^n x_{i1} \cdots x_{in} \right)^n \leq \left(\sum_{i=1}^n x_{i1}^n \right) \cdots \left(\sum_{i=1}^n x_{in}^n \right).$$

ACKNOWLEDGEMENT. This work was partially funded by a grant from the Garg-Kosef.

Special Issue on Modeling Experimental Nonlinear Dynamics and Chaotic Scenarios

Call for Papers

Thinking about nonlinearity in engineering areas, up to the 70s, was focused on intentionally built nonlinear parts in order to improve the operational characteristics of a device or system. Keying, saturation, hysteretic phenomena, and dead zones were added to existing devices increasing their behavior diversity and precision. In this context, an intrinsic nonlinearity was treated just as a linear approximation, around equilibrium points.

Inspired on the rediscovering of the richness of nonlinear and chaotic phenomena, engineers started using analytical tools from "Qualitative Theory of Differential Equations," allowing more precise analysis and synthesis, in order to produce new vital products and services. Bifurcation theory, dynamical systems and chaos started to be part of the mandatory set of tools for design engineers.

This proposed special edition of the *Mathematical Problems in Engineering* aims to provide a picture of the importance of the bifurcation theory, relating it with nonlinear and chaotic dynamics for natural and engineered systems. Ideas of how this dynamics can be captured through precisely tailored real and numerical experiments and understanding by the combination of specific tools that associate dynamical system theory and geometric tools in a very clever, sophisticated, and at the same time simple and unique analytical environment are the subject of this issue, allowing new methods to design high-precision devices and equipment.

Authors should follow the Mathematical Problems in Engineering manuscript format described at <http://www.hindawi.com/journals/mpe/>. Prospective authors should submit an electronic copy of their complete manuscript through the journal Manuscript Tracking System at <http://mts.hindawi.com/> according to the following timetable:

Manuscript Due	December 1, 2008
First Round of Reviews	March 1, 2009
Publication Date	June 1, 2009

Guest Editors

José Roberto Castilho Piqueira, Telecommunication and Control Engineering Department, Polytechnic School, The University of São Paulo, 05508-970 São Paulo, Brazil; piqueira@lac.usp.br

Elbert E. Neher Macau, Laboratório Associado de Matemática Aplicada e Computação (LAC), Instituto Nacional de Pesquisas Espaciais (INPE), São José dos Campos, 12227-010 São Paulo, Brazil ; elbert@lac.inpe.br

Celso Grebogi, Center for Applied Dynamics Research, King's College, University of Aberdeen, Aberdeen AB24 3UE, UK; grebogi@abdn.ac.uk