

GENERALIZATION OF SUM REPRESENTATION FUNCTIONAL EQUATIONS-I

PL. KANNAPPAN

Faculty of Mathematics
University of Waterloo
Waterloo, Ontario, Canada

and

V. SATHYABHAMA

Department of Mathematics
University of Kerala
Trivandrum, Kerala, India

(Received September 20, 1977 and in revised form March 3, 1978)

ABSTRACT. This paper contains the solution of a functional equation which is a generalization of a functional equation arising in a characterization of directed divergence and inaccuracy.

KEY WORDS AND PHRASES. *Functional Equations, Shannon's Entropy, Probability Distributions, and Characterization of Directed Divergence and Inaccuracy.*

AMS (MOS) SUBJECT CLASSIFICATION (1970) CODES. 39A15, 94A15

1. INTRODUCTION.

It was shown in [7] that the properties of symmetry, expansibility and branching (possessed by directed divergence and inaccuracy) lead to a sum representation of the measures which together with the property of additivity leads to the study of the functional equation

$$\sum_{i=1}^n \sum_{j=1}^m f(x_i y_j, u_i v_j) = \sum_{i=1}^n f(x_i, u_i) + \sum_{j=1}^m f(y_j, v_j) \tag{1.1}$$

For more information on (1.1) refer to [2,3,4]. Here we consider the following functional equation,

$$\sum_{i=1}^2 \sum_{j=1}^3 F_{ij}(p_i r_j, q_i s_j) = \sum_{i=1}^2 G_i(p_i, q_i) + \sum_{j=1}^3 H_j(r_j, s_j) \tag{1.2}$$

which is a generalization of the equation (1.1) (for $n=2, m=3$) and solve (1.2) by employing a technique similar to that in [6] used to solve a generalized form similar to (1.1) connected with Shannon's entropy.

2. MAIN RESULTS.

Let $\Delta_n = \{P=(p_1, \dots, p_n) : p_n \geq 0, \sum_{i=1}^n p_i = 1\}$ denote the set of all complete finite n -ary probability distributions. Let $P, Q, \in \Delta_2, R, S \in \Delta_3$. Let $J =]0, 1[x]0, 1[u\{(0, y)\} \cup \{(1, z)\}$ with $y \in]0, 1[$ and $z \in]0, 1[$. Let $F_{ij}, G_i, H_j : J \rightarrow R$ (reals) be measurable in each variable and satisfy the function equation (1.2). We obtain the solution of the functional equation (1.2) through a sequence of auxiliary results, which we state in the following propositions.

REMARK. Here we are solving (1.2) for complete probability distributions, which differs from the previous works [see 2,3 etc.] based on incomplete distributions ($\sum u_i \leq 1, \sum v_j \leq 1$). This fills the existing gap satisfactorily.

PROPOSITION 1. Let $F: J \rightarrow R$ be measurable in each variable and satisfy the functional equation

$$F(p, q) - F(px, qy) - F((1-x)p, (1-y)q) = A(p, q, x, y), \tag{2.1}$$

where

$$A(p_1 + p_2, q_1 + q_2, x, y) = A(p_1, q_1, x, y) + A(p_2, q_2, x, y) \tag{2.2}$$

for every fixed $x, y \in]0, 1[$ and

$$F(1, 1) = 0 .$$

Then the solutions of equation (2.1) are given by:

$$\begin{aligned} F(p,q) &= ap \log p + bp \log q + cq \log q + a'p - a'q, \\ A(p,q,x,y) &= p[aI(x,x) + bI(x,y)] + cqI(y,y), \end{aligned}$$

where

$$I(x,y) := -x \log y - (1-x) \log (1-y).$$

This result follows easily from [5], by verifying that F in (2.1) satisfies (1.1) for $m=2$, $n=3$, by using (2.2) and the condition $F(1,1) = 0$.

PROPOSITION 2. Let $F: J \rightarrow R$ be measurable in each variable and satisfy the functional equation (2.1), where $A(p,q,x,y)$ satisfies (2.2). Then, the solutions of equation (2.1) are given by

$$\begin{aligned} F(p,q) &= ap \log p + bp \log q + cq \log q + c_1p + c_2q, \\ A(p,q,x,y) &= p[aI(x,x) + bI(x,y)] + cqI(y,y). \end{aligned}$$

PROOF. Define $G(p,q) = F(p,q) + dp + eq$, where $d + e = -F(1,1)$.

Since F is measurable in each variable, G is measurable in each variable. Also, $G(p,q)$ satisfies the functional equation (2.1) and $G(1,1) = 0$. Hence, by proposition 1, we have,

$$G(p,q) = ap \log p + bp \log q + cq \log q + a'p - a'q''$$

so that,

$$F(p,q) = ap \log p + bp \log q + cq \log q + c_1p + c_2q,$$

and

$$A(p,q,x,y) = p[aI(x,x) + bI(x,y)] + cqI(y,y).$$

PROPOSITION 3. Let the function $F: J \rightarrow R$ be measurable in each variable and satisfy the equation

$$F(p,q) - F(px,qy) - F((1-x)p, (1-y)q) = A(p,q,x,y) + B(x,y), \quad (2.3)$$

where $(p,q) \rightarrow A(p,q,x,y)$ satisfies (2.2). Then the solutions of equation (2.3) are given by

$$B(x,y) = c_3,$$

$$F(p,q) = ap \log p + bp \log q + cq \log q + c_1 p + c_2 q - c_3,$$

$$A(p,q,x,y) = p[aI(x,x) + bI(x,y)] + cqI(y,y),$$

where $c_3 = -F(0,0)$.

PROOF. Putting $p = 0 = q$ in equation (2.3), we get

$$-F(0,0) = B(x,y),$$

that is,

$$B(x,y) = c_3, \text{ say.}$$

We now define $G(p,q) = F(p,q) + c_3$. Then $G(p,q)$ satisfies the equation (2.1).

Also, since F is measurable in both the variables, G is measurable in both variables.

Hence, by proposition 2, we get

$$G(p,q) = ap \log p + bp \log q + cq \log q + c_1 p + c_2 q,$$

so that

$$F(p,q) = ap \log p + bp \log q + cq \log q + c_1 p + c_2 q - c_3,$$

and

$$A(p,q,x,y) = p[aI(x,x) + bI(x,y)] + cqI(y,y),$$

and the proof of proposition 3 is complete.

PROPOSITION 4. Let $F_i: J \rightarrow R$, ($i = 1,2,3$) be measurable in each variable satisfying the functional equation

$$F_1(p,q) - F_2(px,qy) - F_3((1-x)p, (1-y)q) = A(p,q,x,y) + B(x,y), \quad (2.4)$$

where $(P,q) \rightarrow A(p,q,x,y)$ satisfies (2.2). Then the solutions of equation (2.4)

are given by

$$\begin{aligned}
 F_1(p,q) &= ap \log p + bp \log q + cq \log q + c_1p + c_2q + d_1 \\
 F_2(p,q) &= ap \log p + bp \log q + cq \log q + (c_1-c_3)p + (c_2-c_4)q + d_2, \\
 F_3(p,q) &= ap \log p + bp \log q + cq \log q + (c_1-c_5)p + (c_2-c_6)q + d_3, \\
 A(p,q,x,y) &= p[aI(x,x) + bI(x,y)] + cqI(y,y) + (c_3-c_5)px + \\
 &\quad + (c_4-c_6)qy + c_5p + c_6q, \\
 B(x,y) &= d_1 - d_2 - d_3 .
 \end{aligned}
 \tag{2.5}$$

PROOF. Putting $p=0=q$ in the equation (2.4), we get

$$F_1(0,0) - F_2(0,0) - F_3(0,0) = B(x,y). \tag{2.6}$$

Denoting $F_i(0,0) = d_i (i = 1,2,3)$, (2.6) yields,

$$d_1 - d_2 - d_3 = B(x,y) . \tag{2.7}$$

Equation (2.4) with $x = 1 = y$, by means of (2.7), gives

$$F_1(p,q) - F_2(p,q) - F_3(0,0) = A(p,q,1,1) + d_1 - d_2 - d_3 .$$

That is,

$$F_2(p,q) = F_1(p,q) - A(p,q,1,1) + d_2 - d_1 . \tag{2.8}$$

When $x = 0 = y$, we get from equation (2.4),

$$F_3(p,q) = F_1(p,q) - A(p,q,0,0) + d_3 - d_1 . \tag{2.9}$$

Substituting for F_2 and F_3 from (2.8) and (2.9) into (2.4), we obtain,

$$\begin{aligned}
 F_1(p,q) - F_1(px,qy) - F_1((1-x)p, (1-y)q) &= A(p,q,x,y) - A(px,qy,1,1) - A((1-x)p, \\
 &\quad (1-y)q,0,0) - d_1 = A_1(p,q,x,y) - d_1 , \tag{2.10}
 \end{aligned}$$

where

$$A_1(p,q,x,y) = A(p,q,x,y) - A(px,qy,1,1) - A((1-x)p, (1-y)q,0,0), \tag{2.11}$$

and $(p,q) \rightarrow A_1(p,q,x,y)$ satisfies (2.2).

Hence, applying proposition 3 to equation (2.10), we get

$$\begin{aligned} F_1(p,q) &= ap \log p + bp \log q + cq \log q + c_1p + c_2q + d_1, \\ A_1(p,q,x,y) &= p[aI(x,x) + bI(x,y)] + cqI(y,y), \end{aligned} \quad (2.12)$$

from which using (2.11) we get,

$$A(p,q,x,y) = p[aI(x,x) + bI(x,y)] + A(px,qy,1,1) + A((1-x)p, (1-y)q,0,0). \quad (2.13)$$

Since $F_i(p,q)$ ($i=1,2,3$) is measurable in each variable, $A(p,q,1,1)$ is measurable in the first and the second co-ordinates. Since $(p,q) \rightarrow A(p,q,1,1)$ satisfies the relation (2.2), we have

$$A(p,q,1,1) + A(r,s,1,1) + A(p+r,q+s,1,1), (p,q), (r,s) \in J, p,q,r,s \in [0,1]. \quad (2.14)$$

When $p = 0 = r$, in the equation (2.14), we get

$$A(0,q,1,1) + A(0,s,1,1) = A(0,q+s,1,1), q,s,q+s \in [0,1]. \quad (2.15)$$

Since $A(0,\cdot,1,1)$ is measurable, [1, pp.8-9], we have, $A(0,q,1,1) = c_4q$, where c_4 is an arbitrary constant. If we define $\beta(p,q) = A(p,q,1,1) - c_4q$, then $\beta(0,q) = 0$ and equation (2.14) becomes

$$\beta(p,q) + \beta(r,s) = \beta(p+r,q+s), (p,q), (r,s) \in J, p,q,r,s \in [0,1]. \quad (2.16)$$

Putting $p = 0$ in (2.16), we get

$$\beta(r,s) = \beta(r,q+s), \quad (2.17)$$

that is, $\beta(r,s) = \text{constant}$, independent of s , say $\theta(r)$. Thus, from (2.16) we obtain,

$$\theta(p) + \theta(r) = \theta(p+r), p,r \in [0,1]. \quad (2.18)$$

But $A(p,q,1,1)$ is measurable in the first and second co-ordinates, and hence $\beta(p,q)$ is measurable in p and q , from which it follows that $\theta(p)$ is measurable. Thus, from [1] again we have, $\theta(p) = c_3p$, where c_3 is an arbitrary constant. That is, $\theta(p) = \beta(p,q) = c_3p = A(p,q,1,1) - c_4q$, from which it follows that

$$A(p,q,1,1) = c_3p + c_4q, \tag{2.19}$$

where c_3 and c_4 are arbitrary constants. Similarly, we can show that

$$A(p,q,0,0) = c_5p + c_6q, \tag{2.20}$$

Where c_5 and c_6 are arbitrary constants. From (2.13), (2.19) and (2.20) we get ,

$$\begin{aligned} A(p,q,x,y) &= p[aI(x,x)+bI(x,y)] + c_3px+c_4qy+c_5(1-x)p+c_6(1-y)q + cqI(y,y), \\ &= p[aI(x,x)+bI(x,y)] + (c_3-c_5)px+(c_4-c_6)qy+c_5p+c_6q+cqI(y,y). \end{aligned} \tag{2.21}$$

From (2.8), (2.12) and (2.19) we obtain,

$$F_2(p,q) = ap \log p + bp \log q + cq \log q + (c_1-c_3)p + (c_2-c_4)q + d_2, \tag{2.22}$$

and from (2.9), (2.12) and (2.20) we get,

$$F_3(p,q) = ap \log p + bp \log q + cq \log q + (c_1-c_5)p + (c_2-c_6)q + d_3. \tag{2.23}$$

Now, (2.12), (2.22), (2.23), (2.21) and (2.7) yield the solutions (2.5) and the proof of proposition 4 is complete.

PROPOSITION 5. Let the functions $F_i: J \rightarrow R$ ($i = 1,2,\dots,6$) which are measurable in each variable satisfy the functional equation

$$\begin{aligned} &[F_1(p_1,q_1) - F_2(p_1x,q_1y) - F_3((1-x)p_1,(1-y)q_1)] \\ &+ [F_4(p_2,q_2) - F_5(p_2x,q_2y) - F_6((1-x)p_2,(1-y)q_2)] \\ &= A(p_1+p_2,q_1+q_2,x,y), p_1+p_2 \in [0,1], q_1+q_2 \in [0,1] \end{aligned} \tag{2.24}$$

Then the solutions of the equation (2.24) are given by

$$\left. \begin{aligned} F_1(p,q) &= ap \log p + bp \log q + cq \log q + c_1p + c_2q + d_1, \\ F_2(p,q) &= ap \log p + bp \log q + cq \log q + (c_1-c_3)p + (c_2-c_4)q + d_2, \\ F_3(p,q) &= ap \log p + bp \log q + cq \log q + (c_1-c_5)p + (c_2-c_6)q + d_3, \\ F_4(p,q) &= ap \log p + bp \log q + cq \log q + c'_1p + c'_2q + d_4, \\ F_5(p,q) &= ap \log p + bp \log q + cq \log q + (c'_1-c_3)p + (c'_2-c_4)q + d_5, \\ F_6(p,q) &= ap \log p + bp \log q + cq \log q + (c'_1-c_5)p + (c'_2-c_6)q + d_6, \end{aligned} \right\} \tag{2.25}$$

$$A(p, q, x, y) = p(aI(x, x) + bI(x, y)) + cI(y, y) + (c_3 - c_5)dx + (c_4 - c_6)qy \\ + c_5p + c_6q + d_1 - d_2 - d_3 + d_4 - d_5 - d_6.$$

PROOF. Putting $p_2 = q_2 = 0$ in the equation (2.24), we get,

$$F_1(p_1, q_1) - F_2(p_1x, q_1y) - F_3((1-x)p_1, (1-y)q_1) + F_4(0, 0) \\ - F_5(0, 0) - F_6(0, 0) = A(p_1, q_1, x, y). \quad (2.26)$$

When $p_1 = q_1 = 0$ in (2.24), we have

$$F_4(p_2, q_2) - F_5(p_2x, q_2y) - F_6((1-x)p_2, (1-y)q_2) + F_1(0, 0) \\ - F_2(0, 0) - F_3(0, 0) = A(p_2, q_2, x, y). \quad (2.27)$$

Adding (2.26) and (2.27) and comparing with the equation (2.24), we get

$$A(p_1 + p_2, q_1 + q_2, x, y) + F_1(0, 0) - F_2(0, 0) - F_3(0, 0) + F_4(0, 0) \\ - F_5(0, 0) - F_6(0, 0) = A(p_1, q_1, x, y) + A(p_2, q_2, x, y). \quad (2.28)$$

Denoting $F_i(0, 0) = d_i$ ($i = 1, 2, \dots, 6$) and defining

$$A_1(p, q, x, y) = A(p, q, x, y) - d_1 + d_2 + d_3 - d_4 + d_5 + d_6, \quad (2.29)$$

(2.28) becomes,

$$A_1(p_1 + p_2, q_1 + q_2, x, y) = A_1(p_1, q_1, x, y) + A_1(p_2, q_2, x, y),$$

that is,

$$(p, q) \rightarrow A_1(p, q, x, y)$$

satisfies (2.2). Now from equation (2.26) and (2.27) we get using (2.29),

$$F_1(p_1, q_1) - F_2(p_1x, q_1y) - F_3((1-x)p_1, (1-y)q_1) \\ = A_1(p_1, q_1, x, y) + d_1 - d_2 - d_3, \quad (2.30)$$

and

$$F_4(p_2, q_2) - F_5(p_2x, q_2y) - F_6((1-x)p_2, (1-y)q_2) = A_1(p_2, q_2, x, y) + d_4 - d_5 - d_6, \quad (2.31)$$

where $(p, q) \rightarrow A_1(p, q, x, y)$ satisfies (2.2). Hence, applying proposition 4 separately to the equations (2.30) and (2.31), we get,

$$\left. \begin{aligned} F_1(p, q) &= ap \log p + bp \log q + cq \log q + c_1 p + c_2 q + d_1 \\ F_2(p, q) &= ap \log p + bp \log q + (c_1 - c_3)p + (c_2 - c_4)q + d_2 + cq \log q \\ F_3(p, q) &= ap \log p + bp \log q + (c_1 - c_5)p + (c_2 - c_6)q + d_3 + cq \log q \\ A(p, q, x, y) &= p[aI(x, x) + bI(x, y)] + (c_3 - c_5)px + (c_4 - c_6)qy + cqI(y, y) \\ &\quad + c_5 p + c_6 q + d_1 - d_2 - d_3 + d_4 - d_5 - d_6, \end{aligned} \right\} (2.32)$$

and

$$\left. \begin{aligned} F_4(p, q) &= a'p \log p + b'p \log q + c'q \log q + c'_1 p + c'_2 q + d_4, \\ F_5(p, q) &= a'p \log p + b'p \log q + (c'_1 - c'_3)p + (c'_2 - c'_4)q + d_5 + c'q \log q, \\ F_6(p, q) &= a'p \log p + b'p \log q + (c'_1 - c'_5)px + (c'_2 - c'_6)qy + d_6 + c'q \log q, \\ A(p, q, x, y) &= p[a'I(x, x) + b'I(x, y)] + (c'_3 - c'_5)px + (c'_4 - c'_6)qy + c'qI(y, y) \\ &\quad + c'_5 p + c'_6 q + d_1 - d_2 - d_3 + d_4 - d_5 - d_6. \end{aligned} \right\} (2.33)$$

Comparing the values of A in (2.32) and (2.33) we see that,

$$a' = a, b' = b, c'_3 - c'_5 = c_3 - c_5, c'_4 - c'_6 = c_4 - c_6, c'_5 = c_5, c'_6 = c_6, c' = c.$$

Thus, we have $c'_3 = c_3$ and $c'_4 = c_4$. Hence, from the expressions (2.32) and (2.33), (2.25) follows and the proposition 5 is proved. The converse is also true.

Propositions 1 to 5 lead us to the following main theorem.

THEOREM. Let $F_{ij}, G_i, H_j: J \rightarrow R$ ($i = 1, 2; j = 1, 2, 3$) be functions which are measurable in each variable satisfying the functional equation (1.2). Then the solutions of the equation (1.2) are given by

$$\left. \begin{aligned} H_1(p, q) &= ap \log p + bp \log q + cq \log q + c_1 p + c_2 q + e_1, \\ H_2(p, q) &= ap \log p + bp \log q + cq \log q + c'_1 p + c'_2 q + e_4, \\ H_3(p, q) &= ap \log p + bp \log q + cq \log q + c''_1 p + c''_2 q + e_7, \\ F_{11}(p, q) &= ap \log p + bp \log q + cq \log q + (c_1 - c_3)p + (c_2 - c_4)q + e_2, \end{aligned} \right\} (2.34)$$

$$\left. \begin{aligned}
 F_{12}(p,q) &= ap \log p + bp \log q + cq \log q + (c'_1 - c_3)p + (c'_2 - c_4)q + e_5, \\
 F_{13}(p,q) &= ap \log p + bp \log q + cq \log q + (c''_1 - c_3)p + (c''_2 - c_4)q + e_8, \\
 F_{21}(p,q) &= ap \log p + bp \log q + cq \log q + (c_1 - c_5)p + (c_2 - c_6)q + e_3, \\
 F_{22}(p,q) &= ap \log p + bp \log q + cq \log q + (c'_1 - c_5)p + (c'_2 - c_6)q + e_6, \\
 F_{23}(p,q) &= ap \log p + bp \log q + cq \log q + (c''_1 - c_5)p + (c''_2 - c_6)q + e_9, \\
 G_1(p,q) &= g(p,q), \\
 G_2(p,q) &= e_9 + e_8 - e_7 - g(1-p,1-q) - aI(p,p) - bI(p,q) - cI(q,q) \\
 &\quad - (c_3 - c_5)(1-p) - (c_4 - c_6)(1-q) \\
 &\quad - e_1 + e_2 + e_3 - e_4 + e_5 + e_6 - c_5 - c_6,
 \end{aligned} \right\} (2.34)$$

where $g(p,q)$ is an arbitrary measureable function and e_i ($i = 1, 2, \dots, 9$), a, b, c, c_i ($i = 1, 2, 3, 4$), c'_1, c''_1, c'_2 and c''_2 are arbitrary constants.

PROOF. In the equation (1.2) put $p_1 = p, p_2 = 1-p; q_1 = q, q_2 = 1-q; r_3 = 1-r_2-r_1, s_3 = 1 - s_1 - s_2$. Then we obtain,

$$\begin{aligned}
 & [H_1(r_1, s_1) - F_{11}(pr_1, qs_1) - F_{21}((1-p)r_1, (1-q)s_1)] \\
 & \quad + [H_2(r_2, s_2) - F_{12}(pr_2, qs_2) - F_{22}((1-p)r_2, (1-q)s_2)] \\
 & = [F_{13}(pr_3, qs_3) + F_{23}((1-p)r_3, (1-q)s_3) - H_3(r_3, s_3)] \\
 & \quad - G_1(p, q) - G_2(1-p, 1-q) \\
 & =: A(1-r_3, 1-s_3, p, q), \text{ say.} \tag{2.35}
 \end{aligned}$$

From the identity,

$$\begin{aligned}
 & [H_1(r_1, s_1) - F_{11}(pr_1, qs_1) - F_{21}((1-p)r_1, (1-q)s_1)] \\
 & \quad + [H_2(r_2, s_2) - F_{12}(pr_2, qs_2) - F_{22}((1-p)r_2, (1-q)s_2)] \\
 & = A(r_1+r_2, s_1+s_2, p, q),
 \end{aligned}$$

we deduce from proposition 5 that,

$$\left. \begin{aligned}
 H_1(r,s) &= ar \log r + br \log s + cs \log s + c_1r + c_2s + e_1, \\
 F_{11}(r,s) &= ar \log r + br \log s + cs \log s + (c_1 - c_3)r + (c_2 - c_4)s + e_2,
 \end{aligned} \right\} (2.36)$$

$$\begin{aligned}
 F_{21}(r,s) &= ar \log r + br \log s + cs \log s + (c_1 - c_5)r + (c_2 - c_6)s + e_3, \\
 H_2(r,s) &= ar \log r + br \log s + cs \log s + c_1'r + c_2's + e_4, \\
 F_{12}(r,s) &= ar \log r + br \log s + cs \log s + (c_1' - c_3)r + (c_2' - c_4)s + e_5, \\
 F_{22}(r,s) &= ar \log r + br \log s + cs \log s + (c_1' - c_5)r + (c_2' - c_6)s + e_6, \\
 A(r,s,p,q) &= r[aI(p,p) + bI(p,q)] + (c_3 - c_5)rp + (c_4 - c_6)sq + cI(q,q) \\
 &\quad + c_5r + c_6s + e_1 - e_2 - e_3 + e_4 - e_5 - e_6.
 \end{aligned}
 \tag{2.36}$$

From (2.35) we have, (using (2.36)),

$$\begin{aligned}
 H_3(r_3, s_3) - F_{13}(pr_3, qs_3) - F_{23}((1-p)r_3, (1-q)s_3) \\
 &= -A(1-r_3, 1-s_3, p, q) - G_1(p, q) - G_2(1-p, 1-q), \\
 &= -(1-r_3)[aI(p,p) + bI(p,q)] - c(1-s_3)(q, q) - (c_3 - c_5)(1-r_3)p \\
 &\quad - (c_4 - c_6)(1-s_3)q - c_5(1-r_3) - c_6(1-s_3) \\
 &\quad - e_1 + e_2 + e_3 - e_4 + e_5 + e_6 - G_1(p, q) - G_2(1-p, 1-q). \\
 &= \left\{ r_3[aI(p,p) + bI(p,q)] + pr_3(c_3 - c_5) + (c_4 - c_6)s_3q + cs_3(q, q) \right. \\
 &\quad \left. + c_5r_3 + c_6s_3 \right\} - \left\{ aI(p,p) + bI(p,q) + cI(q,q) + (c_3 - c_5)p \right. \\
 &\quad \left. + (c_4 - c_6)q + c_5 + c_6 + e_1 - e_2 - e_3 + e_4 - e_5 - e_6 \right. \\
 &\quad \left. + G_1(p, q) + G_2(1-p, 1-q) \right\}.
 \end{aligned}
 \tag{2.37}$$

Applying proposition 4 to (2.37), we get

$$\begin{aligned}
 H_3(r,s) &= ar \log r + br \log s + cs \log s + c_1'r + c_2's + e_7, \\
 F_{13}(r,s) &= ar \log r + br \log s + cs \log s + (c_1' - c_3)r + (c_2' - c_4)s + e_8, \\
 F_{23}(r,s) &= ar \log r + br \log s + cs \log s + (c_1' - c_5)r + (c_2' - c_6)s + e_9, \\
 aI(p,p) + bI(p,q) + cI(q,q) + (c_3 - c_5)p + (c_4 - c_6)q + c_5 + c_6 + e_1 - e_2 \\
 &\quad - e_3 + e_4 - e_5 - e_6 + G_1(p, q) + G_2(1-p, 1-q) = e_9 + e_8 - e_7.
 \end{aligned}
 \tag{2.38}$$

Let $G_1(p, q) = g(p, q)$. Then g is measurable in each variable. Thus, from the last expression in (2.38), we get

$$\begin{aligned}
G_2(p,q) = & e_9 + e_8 - e_7 - g(1-p,1-q) - aI(p,p) - bI(p,q) - cI(q,q) \\
& - (c_3 - c_5)(1-p) - (c_4 - c_6)(1-q) - e_1 + e_2 + e_3 \\
& - e_4 + e_5 + e_6 - c_5 - c_6 .
\end{aligned} \tag{2.39}$$

Now (2.36), (2.38) and (2.39) give the solutions (2.34). This completes the proof of the theorem.

One can easily verify that the eleven functions given by the expressions (2.34) satisfy the functional equation (1.2).

3. APPLICATION.

As pointed out in section one, from the solutions of the functional equation (1.2) and the sum representation of the measures and some initial conditions [2], we can obtain the measures the directed divergence and the inaccuracy.

ADDITION: REMARK. In almost every characterization of the measures, the Shannon entropy, the directed divergence, the inaccuracy etc., several functional equations are used to achieve the result. In one set of characterizations, one comes across equations of the type

$$(*) \quad f(x) + (1-x)f\left(\frac{y}{1-x}\right) = f(y) + (1-y)f\left(\frac{x}{1-y}\right)$$

and in the other, one comes across the functional equations of the type (1.1).

Recently, in dealing with the mixed theory of information (as distinguished from the probabilistic and nonprobabilistic theories), we came across generalization of (*) of the form

$$f(x) + (1-x)g\left(\frac{y}{1-x}\right) = h(y) + (1-y)k\left(\frac{x}{1-y}\right) .$$

In a similar manner, while considering sum representation forms in the mixed theory of information, one might have to deal with functional equations of the form (1.2), which is a generalization of the form (1.1)

ACKNOWLEDGMENT. This research is partially supported by a NSERC of Canada grant.

REFERENCES

1. Aczel, J., and Z. Daroczy, On measures of information and their characterizations, Academic Press, (1975).
2. Kannappan, PL., On Shannon's entropy, directed divergence and inaccuracy, Z. Wahr. Verw. Geb. 22 (1972) 95-100.
3. Kannappan, PL., On directed divergence and inaccuracy, Z. Wahr. Verw. Geb. 25 (1972) 49-55.
4. Kannappan, PL., On the Measurable Solutions of two functional equations, Mathamatica Cluj., 16 (39) (1974), no 2 (1977), 275-280.
5. Kannappan, PL., and P. N. Rathie, On the measureable solution of a functional equation in two variables (to appear).
6. Ng, C. T., On the Measurable solutions of the functional equation

$$\sum_{i=1}^2 \sum_{j=1}^3 F_{i,j}(p, q_j) = \sum_{i=1}^2 G_i(p_i) + \sum_{j=1}^3 H_j(q_j),$$
Acta Math. Acad. Sci. Hungar. 25 (1974) 249-254.
7. Ng. C. T., Representation for measures of information with the branching property, Information and Control 25 (1974) 45-56.

Special Issue on Time-Dependent Billiards

Call for Papers

This subject has been extensively studied in the past years for one-, two-, and three-dimensional space. Additionally, such dynamical systems can exhibit a very important and still unexplained phenomenon, called as the Fermi acceleration phenomenon. Basically, the phenomenon of Fermi acceleration (FA) is a process in which a classical particle can acquire unbounded energy from collisions with a heavy moving wall. This phenomenon was originally proposed by Enrico Fermi in 1949 as a possible explanation of the origin of the large energies of the cosmic particles. His original model was then modified and considered under different approaches and using many versions. Moreover, applications of FA have been of a large broad interest in many different fields of science including plasma physics, astrophysics, atomic physics, optics, and time-dependent billiard problems and they are useful for controlling chaos in Engineering and dynamical systems exhibiting chaos (both conservative and dissipative chaos).

We intend to publish in this special issue papers reporting research on time-dependent billiards. The topic includes both conservative and dissipative dynamics. Papers discussing dynamical properties, statistical and mathematical results, stability investigation of the phase space structure, the phenomenon of Fermi acceleration, conditions for having suppression of Fermi acceleration, and computational and numerical methods for exploring these structures and applications are welcome.

To be acceptable for publication in the special issue of Mathematical Problems in Engineering, papers must make significant, original, and correct contributions to one or more of the topics above mentioned. Mathematical papers regarding the topics above are also welcome.

Authors should follow the Mathematical Problems in Engineering manuscript format described at <http://www.hindawi.com/journals/mpe/>. Prospective authors should submit an electronic copy of their complete manuscript through the journal Manuscript Tracking System at <http://mts.hindawi.com/> according to the following timetable:

Manuscript Due	December 1, 2008
First Round of Reviews	March 1, 2009
Publication Date	June 1, 2009

Guest Editors

Edson Denis Leonel, Departamento de Estatística, Matemática Aplicada e Computação, Instituto de Geociências e Ciências Exatas, Universidade Estadual Paulista, Avenida 24A, 1515 Bela Vista, 13506-700 Rio Claro, SP, Brazil ; edleonel@rc.unesp.br

Alexander Loskutov, Physics Faculty, Moscow State University, Vorob'evy Gory, Moscow 119992, Russia; loskutov@chaos.phys.msu.ru